



# DELTA

## DELTA JEEP® COMBO GROUND BAR With 3 Built-in Lighting Systems for JEEP Wrangler JK & TJ 1997-2008 P/N 01-9562-7BX INSTALLATION INSTRUCTION

1. Install (3) relays in a close proximity to the battery.
2. Connect black wires leading from relays to metal surface under the hood with a sheet metal screw (provided).
3. Run the longer part of the harness toward the passenger side of the front bumper using cable ties (provided).
4. Remove (2) floodlights, (rock-crawling lights) on both ends of the Combo Ground Bar to facilitate installation.
5. Using existing factory bolts attach the DELTA Combo Ground Bar to the bumper (applies to TJ)
6. Using two ½" .bolts (not provided) attach the Combo Ground Bar to the frame (applies to JK) see photo.
7. Re-install (2) remaining floodlights into the Combo Bar.
8. Connect the Combo Bar into the harness using waterproof connectors.
9. Install (2) switches at a desired location inside your vehicle.
10. Connect blue wires (double wire coil) one to each exterior prong on the dual-switch.
11. Connect the short red wire from the middle prong on the dual-switch to any "hot wire" using snap-lock (provided).
12. Connect the remaining blue wire to one prong on the single-switch.
13. Connect the other prong of the switch using the short red wire to any "hot wire" using snap-connector (provided).
14. Connect (3) red wires leading from relays under the hood to the battery.

You may now test your lights! **HAPPY FOUR WHEELING!**

**DRIVING LIGHTS** – for long range illumination

**FOG LIGHTS** – for cornering or short range peripheral coverage in obscure weather condition

**ROCK-CRAWLER LIGHTS** – for ground illumination in front of your front wheels



**PATENT PENDING**



**MADE IN USA**

**DELTA TECH INDUSTRIES, LLC - Placentia, CA 92870, U.S.A.**

Web: [www.deltalights.com](http://www.deltalights.com) E-mail: [sales@deltatechindustries.com](mailto:sales@deltatechindustries.com)

CONTENS::

- (1) Combo Bar with Harness
- (1) Dual-Switch
- (1) Sgl. Switch
- (2) Snap-lock connectors
- (2) Red wires
- (8) wire ties
- (4) screws